
SAP E & C PLC BASED SCADA SYSTEM TRAINER (PRODUCT CODE: SAP - 89)





- The PLC Based SCADA System Simulator Trainer (SAP - 89) outlines the principle of SCADA System used in Industrial Environment.
- The Static Application Panels provide an idea of different Process Plants.
- The Static Application Panels mounted on MS Powder Coated Frame and are detachable as per user's requirement.

Technical Specification:

No.	Item Name	Technical Specifications
140.	item Name	
		A] PLC PANEL/ LOCAL CONTROL STATIONS:
	All digital as	well as Analog I/Os are brought out on these panels for easy connection.
1	PLC-	1No., Allen-Bradley Micrologix 1400 L32BXBA/Siemens S7 200Smart/Eqvt,
		8 Point Ethernet Switch. Digital inputs: 20, Digital outputs: 12
		Analog Inputs: 4, Analog Outputs: 2
		RS LOGIX Software: 1 NO., Ladder diagram programming on PC.
		RS LOGIX 500 MICRO STARTER 9324RLM0100ENE.
		Communication- RS 232 / RS 485 / Ethernet/ TCP-IP.
2	Power Supply-	24 V DC, 3 A, Size: 4" (L) X 2" (W) X 2" (H).
3	Interface Facility-	PC interface facility. PC-PLC interfacing cable1761-CBL-PM02
4	RS 485 / RS 232	For Converting RS485 Signals (If RS 485 protocol is used) into RS232 signals.
	Converter-	
5	Electrical Control Panel-	MS Powder coated panel with switches, indicator, Test Points, controller on front fascia, UK 2.5 Terminal Connectors mounted on DIN rail channel. Use of 1sq mm multi- strand wire with Proper insulated Lugs, Ferruling & neat wire Dressing & clamping Wires & power cables are Seated through 1"×1" PVC cable tray. Input - Output LED indication on front panel.
		Necessary Input -Output simulating devices. Front panel for display of digital I/O status: Lamps (14no.),
		LED Indicators (10no.)

SAP E & C PLC BASED SCADA SYSTEM TRAINER (PRODUCT CODE: SAP - 89)



6 SCADA Application Software - Above PLC can be turned into SCADA Trainer using PC Based SCADA Appli Software. SCADA Application Software with 75 Tags is provided for Simula following 19 Static Application Panels. RS View 75 Tags SCADA Application S/W, PID setting (P, PI And PID mode) Auto/Manual Tuning of PID, Software Data Storage, Off Line analysis, Onl Acquisition, Simulation and Printing of data in Graphical and tabular form Interactive Graphical User Interface (GUI) includes. 7 Computer PC with color monitor: 15", PC Pentium Dual Core/i3, with serial commu ports,250/500 GB HDD, 2 GB RAM. C] STATIC APPLICATION PANELS: [To be hooked up with PLC Trainer – (PCST – 14)] Simulating Modules consisting of Display on Mimic mounted on M.S. Powder Coated Frame with Interaction
C] STATIC APPLICATION PANELS: [To be hooked up with PLC Trainer – (PCST – 14)] Simulating Modules consisting of Display on Mimic mounted on M.S. Powder Coated Frame with Ind
Simulating Modules consisting of Display on Mimic mounted on M.S. Powder Coated Frame with In-
Input-Output & Toggle Switches. * These Modules can be purchased either individually or collectively 1) Oven Control 2) Bottling Plant 3) Parking Garage 4) Combination Lock 5) Elevator Simulator 6) Silo Control 7) Alarm Actuation 8) Motor Starter Control 9) Resistance Welding 10) Sequential Control Of Motors 11) Soft Drink Dispensing Machine 12) Star Delta Control 13) Seven Segment Display 14) Switching Of Lamps 15) Tank Level Control 16) Traffic Light Control 17) Washing Machine 18) Reaction Vessel 19) Process (Ph) Control Trainer D] M.S. Powder Coated Frame for Mounting Eight Static Application Panels & for Supervisory Station
E] HMI (Optional)

Range of experiments-

- ✤ Auxiliary Experiments.
- Study of Hierarchical control system.
- Study of SCADA Application Software.

SAP E & C PLC BASED SCADA SYSTEM TRAINER (PRODUCT CODE: SAP - 89)



Features-

- Compact Ergonomic Design.
- User Friendly, Self Explanatory Systems.
- Leak proof safety Measures, sturdy piping.
- Enhanced Electrical Safety Considerations.
- Training Manuals & mimic Charts for Operation Ease.
- System Frame with Caster Wheel Arrangement for ease in movement.
- M.S. powder coated cubical plant with standard Instrument Mountings.
- Inbuilt safety Measures to avoid improper usage.

Services Required:

Electrical supply of 1φ 230V 50Hz.

Note:

All descriptive matter and illustrations are intended to give only a general idea of the equipment detailed specifications may be altered at the company's discretion without any notice.

	Manufactured/Marketed By
	SAP ENGINEERS & CONSULTANTS
Regd. Off.	: Shop No. 26-27, 'Srushti', Survey No.82, Near Guru Ganesh Nagar, Eklavya College Road (D.P.Road), Kothrud, Pune - 411 038, India
Telephone	: (020) 2538 4737
Mobile	: +91 94220 88946, +91 9552475082
Fax	: (020) 2538 3544
Email	: sales@sapengineers.com
Website	: www.sapengineers.com / www.sapengineers.co.in